



4G Wi-Fi Wireless Router

## **WIS-N300-LTE**

WIS Networks Limited

[www.wis.us](http://www.wis.us)

E-mail: [sales@wis.us](mailto:sales@wis.us)

Version 1.0

## Product Overview

The WIS-N300-LTE Take full advantage of your cutting-edge 4G LTE network to download speed up to 150 Mbps. Share your 4G LTE network with multiple Wi-Fi devices and enjoy uninterrupted HD movies, rapid file downloads, and smooth video chats. Fully compatible with FDD-LTE and TDD-LTE to work with most service providers worldwide.

## Features

### Hardware

- Cutting-edge 4G network – Share internet access with up to 32 Wi-Fi devices
- Share internet access with up to 32 Wi-Fi devices
- Wi-Fi router mode – Plug an Ethernet cable into the LAN/WAN port for flexible access if you can't get a 4G connection
- 2 x 4G LTE Antennas + 2 x Wi-Fi Antennas
- IEEE 802.11b/g/n Wi-Fi



## Plug and Play!

With an integrated 4G LTE modem and a built-in SIM card slot, all you need to do is inserting a micro SIM card and turning on the router. It has never been easier than enjoy a fast, stable Wi-Fi on 4G LTE network.

## Specifications

Model	WIS-N300-LTE
4G Cartgory	LTE CAT.4
Max 4G speed	DL:150Mbps UL:50Mbps
Network Type	4G: FDD-LTE: B1/B3/B5/B7/B8/B20 (2100/1800/850/2600/900/800 MHz) TDD-LTE: B38/B40/B41 (2600/2300/2500 MHz) 3G: HSPA/UMTS: B1/B5/B8 (2100/850/900 MHz)
Frequency	2.4 GHz
Wireless standards	802.11b/g/n
Channel Bandwidth	20 MHz, 40MHz
Memory	64MB SDRAM
Flash	16MB
Antenna	2× 4G LTE Antennas + 2*Wi-Fi Antennas
Max Output Power	20±3 dBm
Number of SIM slots	1
WAN Port	1*10/100auto-sensing, auto-MDX
LAN Port	2*10/100auto-sensing, auto-MDX
Reset Button	Press for 10 seconds to restore the router to its factory settings
LEDs	Power/SYS/POE
Active Users	32
External Power Supply	12V / 1A
Dimension	185*126*60mm
Weight	About 300g
Temperature	Operating Temperature: 0°C~40°C (32°F ~104°F) Storage Temperature: -40°C~70°C (-40°F ~158°F)
Humidity	Operating Humidity: 10%~90% non-condensing Storage Humidity: 5%~90% non-condensing
Certification	CE, RoHS